### **BY ACCURATUS**



# 1 2 3 4 5 ↑ ▷ R OK 6 7 8 9 0 ↑ ← DEL

## Accuratus KYB500-BB20A

#### ۸ ام م. . <del>د</del>

The Accuratus 20 key bump bar is designed to work seamlessly with your kitchen interface, making sorting through orders easier than ever. Use the intuative design to accept, move, and fulfil orders quickly and easily, without having to touch screens and other equipment where grease and dirt can build up. The bump bar can be customised with your own colour, legends, interfaces, and logos to create a bump bar tailored to you and your needs.

# Specifications -

- Combo USB & RF Wireless 2.4GHz interface (USB receiver included.
- When in RF mode 2 x AA batteries are required (batteries not included).
- Fully programmable 20 key solution.
- Includes easy to remove paper legend to customise keys.
- · Using durable metal dome structure mechanical keys with a sealed membrane input.
- Rugged industrial strong and robust plastic housing
- 50 million actuations per key.
- Spill proof designed top surface.
- Detacabble RJ45 cable, designed to be easily replaced if required
- On request the keys can be altered to double or quad size.
- Rear metal backing plate designed with vertical or horizontal mounting holes
- Total mechanical travel: 0.8mm.
- Input voltage: 2V/3V.
- Working current: 5mA.
- Sleeping current: 30uA.
- Power Supply:  $+5V/DC \pm 5\%$ .
- Input: <100mA.
- MTBF: 50,000 hours. Country of origin: China

# **Physical Specifications**

- Dimensions: 75x253x26mm
- Weight: 0.7 kg





